

GE RF Preamplifier 1313-A1840



Features

- > Noise Figure ≤ 3.0 dB
- > Unconditionally Stable at all Temperatures
- > Internally Regulated DC Voltage
- > 50 Ohm Matched Input/Output
- > Field Replaceable 2.92mm K Connectors
- > Excellent Group Delay and Phase Linearity
- > 0.009 Inches Diameter RF In/Out Feed Through
- > Operating Temp. - 55 C to +85 C
- > 3 Year Warranty

Options

- > Optimized Performance over Selected Bandwidth
- > Internally DC Block Input (Output DC Block Standard)
- > Hermetically Sealed Package
- > Improved Gain Flatness
- > Improved IN and OUT VSWR
- > Gain and Phase matching
- > Lower Noise Figure

Specifications (23 °C)

All specifications are subject to change without notice.
All values are typical, unless specified.

Parameter	Min	Typ	Max	Units
Frequency Range	18	-	40	GHz
Noise Figure*	-	2.9	3	dB
Gain	48	50	-	dB
Gain Flatness (+/-)	-	± 2.5	± 3	dB
P1 Output Power	+8	+10	-	dBm
Input VSWR	-	-	2.5:1	
Output VSWR	-	-	2.5:1	
Operating Temperature	-55	-	+85	°C
Non - Operating Temp Range	-65	-	+85	°C
RF Input Power (no - damage)	-	-	+13	dBm

GE RF Preamplifier 1313-A1840

Specifications (23 °C)

All specifications are subject to change without notice.
 All values are typical, unless specified.

Parameter	Min	Typ	Max	Units
Humidity (non - condensing)	-	-	95	%
Voltage	+8	+12	+15	VDC
Current	-	250		mA
Input Impedance		50		Ohms
RF Connector		2.92mm - Female		
Dimensions		132.9 x 120 x 69.1		mm

* Noise source used for measurement from 18GHz to 42 GHz is HP346C-K01 .

NF uncertainty (approx. 0.3 dB). 0.2 dB due to ENR of HP 346C-K01, and 0.1 dB due to the gain modulation of the unit caused by the HP 346C-K01 source impedance change in the ON and OFF state.

Typical Data

